

WAXIE SNAP & GO MAGNETIC MODULES

LED Linear Retrofit Kits for Fluorescent Fixtures

TECHNICAL DATA SHEET



The Easiest Conversion to LED Available

Features


- Simple modification of existing fluorescent fixtures to LED
- Quick connect requires virtually no tools
- Significantly easier than changing a ballast
- Magnetic mounting
- Shatterproof and mercury-free
- Innovative patented design

Application

- Retrofit existing fluorescent fixtures and recessed troffers
- Easily modify existing fixtures to LED without replacing entire fixture
- Available in various sizes, wattages and colors for nearly all fluorescent fixtures
- Less expensive than replacing a fixture
- More than twice the life of conventional fluorescent lamps
- 120/277 Volt capability


WAXIE Snap & Go Magnetic Modules LED Linear Retrofit Kits for Fluorescent Fixtures

PRODUCT DETAILS

Electrical		Environment		Construction	
Wattage	40W	Operating Temperature	-25° ~ 40°C	Housing	Plastic
Voltage	110-277V	Suitable Location		Base / Power Supply	Hard Wired
Current	0.355A	Ingress Protection Rating	IP20	Lens	Frosted
Power Factor	0.9	Fixture Type	Enclosed	Packaging	
Total Harmonic Distortion (thd)	18	Certifications		Master Carton	10pc / 10811768028642
Lighting Performance				Individual Box	811768028645
Lumens	5200			Country of Origin	China
Lumens Per Watt (Lm/W)	130			HS Tariff	9405.40.6000
Color Temperature (cct)	4000K	Lifespan		Driver	
Color Rendering (Cri)	80	Average Life (Hours)	50,000	Driver Dimension (Inches)	5.7"(L) × 1.7(W) × 1.1"(H)
Beam Angle	140°	Warranty (Years)	5		
Light Distribution	Type VS	Components			
Dimmable Lighting Control		LED Light Source	SMD2835		

Dimensions

Dimensions (inches) 43.3"(L) × 0.5"(W) × 0.2"(H)



ORDERING

Item #	MFI #	Description	Watt	Color	Lumens	CRI	Volt	Hours	Case	Product Image
555175	93680	WAXIE LED Snap & Go Magnetic Module/ 40w/4000k/Frosted Lens 2 × 48" DLC	40	4000K	5200	80	110 - 277	50,000	10	